

CAS LP-1000N Programming

Get into Programming Mode: [CLEAR] 1 [MODE]

Store Name: press ↑ (3 time) to SHOP then press [PRT/*]

1. Enter 1st line then press [ENTER],
2. Enter 2nd line then press [ENTER], then [PRT/*], [CLEAR]

Date: press ↑ (2 time) to SET then press [PRT/*]

1. Press 1 then [PRT/*]
2. Enter (*New DATE*) then press [PRT/*], [CLEAR]

Time: press ↑ (2 time) to SET then press [PRT/*]

1. Press 2 then [PRT/*]
2. Enter (*New TIME*) then press [PRT/*], [CLEAR]

PLU Programming: [CLEAR] 1 [MODE] then [PRT/*]

1. Enter (*PLU#*) then [PRT/*]
2. **ICODE** = If want to put barcode number
3. **NAME** = [PRT/*], enter the PLU name here then [PRT/*]
4. **MSGno** = For link up to Ingredients(link MSG # with PLU)
5. **PRICE** = Enter \$\$\$\$ then [PRT/*]. ****MUST ENTER PRICE HERE****
6. **LIFE** = If you want to put a shelf life time from date of packing.
7. **TARE** = Enter the auto tare weight to take out (-)
8. **GCODE** = For group code
9. **SAVE** = Press [PRT/*] to save changes(printout)

Ingredients Programming: [CLEAR] 1 [MODE] then [PRT/*]

1. Press ↑ (2 time) to SET then press [PRT/*]
2. Enter (*MSG#*) then [PRT/*], [PRT/*]
3. Type 1st line Message then [ENTER]
4. Type 2nd line Message then [ENTER], (*UP TO 8 LINES*)
5. Press [PRT/*], [CLEAR]

Label Type: press ↑ (2 time) to SET then press [PRT/*]

1. Press 4, then [PRT/*] then press 1
2. Enter (*Label length*) then [PRT/*] then, [CLEAR]
3. *Label Length:*
 - 30 = LST8000
 - 40 = LST8010, TEC2810
 - 60 = LST8020
 - 35 = LST3600
 - 54 = TEC2730
 - 51 = TEC4900

Label Format: press \uparrow (2 time) to SET then press [PRT/*]

1. Press 4, then [PRT/*] then press 2
2. Enter (*Format#*) then [PRT/*] then [CLEAR]
3. *Format #*: see page 69-71 in manual

Label Print Options: press \uparrow (2 time) to SET then press [PRT/*]

1. Press 4, then [PRT/*] then press 3
2. Enter (*Mask Code*) then [PRT/*] then [CLEAR]
3. *MASK CODE*:
 - D7DF = NO TARE & GROUP
 - D7CF = NO SELL BY DATE, TARE & GROUP
 - D7C7 = NO PACK ON DATE, SELL BY DATE, TARE & GROUP

Label Adjust: [CLEAR] 1 [MODE] then [PRT/*]

1. Press \uparrow (2 time) to SET then press [PRT/*], then 5 [PRT/*]
2. Enter (*Adjust#*) [PRT/*], then enter (*Feed#*) [PRT/*].

	LABEL FORMAT	LABEL LENGTH	ADJUST	FEED
LST8000	1,2,3	30	25	60
LST8010	0,10,11,12	40	15	60
LST8020	22,23	60	30	60
LST8030	1,2,3	30	125	30
LST8040	0,10,11,12	50	95	30

****CHANGE ADJUST WITH -5 OR+5****

Temporary Price Change on PLU: **MUST CHANGE**

1. Press \uparrow (2 time) to SET then press [PRT/*]
2. Press 6 [PRT/*], then 1 [PRT/*], [PRT/*], [CLEAR]

SENSOR TESTING: [CLEAR] 1 [MODE] then [PRT/*]

1. Press \uparrow (2 time) to SET then press [PRT/*]
2. Press 12, then [PRT/*]
3. **POFF** = test peel sensor
4. **HEAD** = ****DO NOT CHANGE****
5. **PEND** = test inside label sensor
6. **HEADUP** = test headup sensor
7. Then [CLEAR]